

SECTION 16195 - ELECTRICAL IDENTIFICATION

PART 1 - GENERAL

1.01 One copy of the electrical distribution diagram and fire alarm system diagram shall be located at the main distribution equipment.

1.02 Distribution Panels, Starters, Disconnect Switches, Circuit Breakers

1. All electrical devices including distribution panels, starters, disconnect switches, circuit breakers shall be identified by one of the following methods or as directed by the Owner.
  - a. with laminated black with white letters phenolic plates engraved all letters shall be a minimum of ¼" high.
  - b. with white letters on black vinyl versa labels by Brady all letters shall be a minimum of ¼" high.

Example:

Line 1 - LPI-N, PPI-N  
Line 2 – 208Y/120V - 3 phase 4W  
Use Brady markers to identify feeders with size and source.

<u>Starters</u>	<u>Circuit Breakers</u>	<u>Disconnect Switches</u>
Line 1	Supply Fan S-1	
Line 2	208V 3 ph PPI-N	

1.03 Compartmental Transformers

1. Pad-mounted transformers shall be identified in upper left-hand corner by one of the following methods or as directed by the Owner.
  - a. with 2" high, yellow stenciled letters by Brady
  - b. with 4" black on yellow versa labels by Brady

Line 1 - Primary voltage - 4160V  
Line 2 - Secondary voltage - 208Y/120V  
Line 3 - Capacity - 300 KVA 3 phase 4W

UNIVERSITY OF NEW HAMPSHIRE  
CONSTRUCTION AND RENOVATION STANDARDS

2. All pad mounted transformers shall have a vinyl sign attached to the main access door the sign shall be a minimum of 10"x14" and state DANGER HIGH VOLTAGE.

PART 2- PRODUCT

2.01 Labels Brady

2.02 Signs Brady

END OF SECTION